

S2LET: A code to perform fast wavelet analysis on the sphere

B. Leistedt¹, J. D. McEwen², P. Vanderghelynst³, and Y. Wiaux⁴

¹ Department of Physics and Astronomy, University College London, London WC1E 6BT, UK
e-mail: boris.leistedt.11@ucl.ac.uk

² Department of Physics and Astronomy, University College London, London WC1E 6BT, UK
e-mail: jason.mcewen@ucl.ac.uk

³ Institute of Electrical Engineering, Ecole Polytechnique Fédérale de Lausanne (EPFL), CH-1015 Lausanne, Switzerland
e-mail: pierre.vanderghelynst@epfl.ch

⁴ Institute of Electrical Engineering, Ecole Polytechnique Fédérale de Lausanne (EPFL), CH-1015 Lausanne, Switzerland
Department of Radiology and Medical Informatics, University of Geneva (UniGE), CH-1211 Geneva, Switzerland
Department of Medical Radiology, Lausanne University Hospital (CHUV), CH-1011 Lausanne, Switzerland
e-mail: yves.wiaux@epfl.ch

Received —; accepted —

ABSTRACT

We describe S2LET, a fast and robust implementation of the scale-discretised wavelet transform on the sphere. Wavelets are constructed through a tiling of the harmonic line and can be used to probe spatially localised, scale-depended features of signals on the sphere. The scale-discretised wavelet transform was developed previously and reduces to the needlet transform in the axisymmetric case. The reconstruction of a signal from its wavelets coefficients is made exact here through the use of a sampling theorem on the sphere. Moreover, a multiresolution algorithm is presented to capture all information of each wavelet scale in the minimal number of samples on the sphere. In addition S2LET supports the HEALPix pixelisation scheme, in which case the transform is not exact but nevertheless achieves good numerical accuracy. The core routines of S2LET are written in C and have interfaces in Matlab, IDL and Java. Real signals can be written to and read from FITS files and plotted as Mollweide projections. The S2LET code is made publicly available, is extensively documented, and ships with several examples in the four languages supported. At present the code is restricted to axisymmetric wavelets but will be extended to directional, steerable wavelets in a future release.

Key words. wavelets on the sphere – harmonic analysis – sampling theorems

1. Introduction

Signals defined or measured on the sphere arise in numerous disciplines, where analysis techniques defined explicitly on the sphere are now in common use. In particular, wavelets on the sphere (Antoine & Vanderghelynst 1998, 1999; Baldi et al. 2009; Marinucci et al. 2008; McEwen et al. 2006; Narcowich et al. 2006; Starck et al. 2006a; Wiaux et al. 2006, 2005, 2007, 2008; Yeo et al. 2008) have been applied very successfully to problems in astrophysics and cosmology, where data-sets are increasingly large and need to be analysed at high resolution in order to confront accurate theoretical predictions (e.g. Barreiro et al. 2000; Basak & Delabrouille 2012; Cayón et al. 2001; Deriaz et al. 2012; Labatie et al. 2012; Lan & Marinucci 2008; McEwen et al. 2006, 2007a,b, 2008; Pietrobon et al. 2008; Starck et al. 2006b; Schmitt et al. 2010; Vielva et al. 2004, 2006a,b, 2007; Wiaux et al. 2006, 2008).

While wavelet theory is well established in Euclidean space (see e.g. Daubechies (1992)), multiple wavelet frameworks have been developed on the sphere, only a fraction of which lead to exact transforms in both the continuous and discrete settings. In fact, discrete methodologies (Schröder & Sweldens 1995; Sweldens 1996, 1997) achieve exactness in practice but may not lead to a stable basis on the sphere (Sweldens 1997). In the continuous setting several constructions are theoretically exact, and have been combined with sampling theorems on the sphere to enable exact reconstruction in the discrete setting also. In particular, scale-discretised wavelets (Wiaux et al. 2008) lean on a

tiling of the harmonic line to yield an exact wavelet transform in both the continuous and discrete settings. In the axisymmetric case, the scale-discretised wavelets (Wiaux et al. 2008) reduce to needlets (Narcowich et al. 2006; Baldi et al. 2009; Marinucci et al. 2008), which were developed independently using a similar tiling of the harmonic line.

In this paper we describe the new publicly available S2LET¹ code to perform the scale-discretised wavelet transform of complex signals on the sphere. At present S2LET is restricted to axisymmetric wavelets (i.e. azimuthally symmetric when centred on the poles) and includes generating functions for both axisymmetric scale-discretised wavelets (Wiaux et al. 2008) and needlets (Narcowich et al. 2006; Baldi et al. 2009; Marinucci et al. 2008). We intend to extend the code to directional, steerable wavelets and spin functions in a future release. The core routines of S2LET are written in C, exploit fast algorithms on the sphere, and have interfaces in Matlab, IDL and Java. We note that public codes are already available to compute scale-discretised (S2DW²; Wiaux et al. 2008) and needlet (NeedATool³; Pietrobon et al. 2010) transforms. We envisage S2LET will supersede S2DW once it is extended to directional, steerable wavelets and spin functions.

The remainder of this article is organised as follows. In section 2 we detail the construction of scale-discretised axisym-

¹ <http://www.s2let.org/>

² <http://www.jasonmcewen.org/>

³ <http://www.fisica.uniroma2.it/~pietrobon/>

metric wavelets and the corresponding exact scale-discretised wavelet transform on the sphere. In section 3 we describe the S2LET code, including implementation details, computational complexity and numerical performance. We present a number of simple examples using S2LET in section 4, along with the code to execute them. We conclude in section 5.

2. Wavelets on the sphere

We review scale-discretised wavelets on the sphere, as considered previously by Wiaux et al. (2008). Directional, steerable wavelets were also considered by Wiaux et al. (2008), however we restrict our attention to axisymmetric wavelets here. The use of a sampling theorem on the sphere guarantees that spherical harmonic coefficients capture all the information content of band-limited signals, resulting in exact harmonic and wavelet transforms; hence, we recall harmonic analysis on the sphere concisely. One may alternatively adopt samplings of the sphere for which exact quadrature rules do not exist such as HEALPIX (Górski et al. 2005), but which nevertheless exhibit other useful properties, leading to numerically accurate but not theoretically exact transforms.

2.1. Harmonic analysis on the sphere

The spherical harmonic decomposition of a square integrable signal $f \in L^2(S^2)$ on the two-dimensional sphere S^2 reads

$$f(\omega) = \sum_{\ell=0}^{\infty} \sum_{m=-\ell}^{\ell} f_{\ell m} Y_{\ell m}(\omega), \quad (1)$$

where $Y_{\ell m}$ are the spherical harmonic functions, which form the canonical orthogonal basis on S^2 . The spherical harmonic coefficients $f_{\ell m}$, with $\ell \in \mathbb{N}$ such that $\ell < \infty$ and $m \in \mathbb{Z}$ such that $|m| \leq \ell$, form a dual representation of the signal f in the harmonic basis on the sphere. The angular position $\omega = (\theta, \phi) \in S^2$ is specified by colatitude $\theta \in [0, \pi]$ and longitude $\phi \in [0, 2\pi]$. The spherical harmonic coefficients are given by

$$f_{\ell m} = \langle f | Y_{\ell m} \rangle = \int_{S^2} d\Omega(\omega) f(\omega) Y_{\ell m}^*(\omega), \quad (2)$$

with the surface element $d\Omega(\omega) = \sin \theta d\theta d\phi$. The signal f is band-limited in the spherical harmonic basis with band-limit L if $f_{\ell m} = 0$, $\forall \ell \geq L$. For band-limited signals sampling theorems can be invoked so that both forward and inverse transforms can be reduced to finite summations that are theoretically exact. Sampling theorems effectively encode a quadrature rule for the exact evaluation of integrals on the sphere from a finite set of sampling nodes. Various sampling theorems exist in the literature (e.g. Driscoll & Healy 1994; Healy et al. 1996; McEwen & Wiaux 2011). In this work we adopt the McEwen & Wiaux (2011) sampling theorem (hereafter MW), which is based on an equiangular sampling scheme and, for a given band-limit L , requires the lowest number of samples on the sphere of all sampling theorems, namely $(L-1)(2L-1)+1 \sim 2L^2$ samples (for comparison $\sim 4L^2$ samples are required by Driscoll & Healy (1994)). Fast algorithms to compute the corresponding spherical harmonic transform scale as $\mathcal{O}(L^3)$ and are numerically stable to band-limits of at least $L = 4096$ (McEwen & Wiaux 2011). Alternative sampling schemes that are not based on sampling theorems also exist, such as HEALPIX (Górski et al. 2005) or GLESP (Doroshkevich et al. 2005). However, these schemes do not lead to exact spherical harmonic transforms on the sphere.

Nevertheless the resulting approximate transforms achieve good accuracy and benefit from other practical advantages, such as equal-area pixels.

2.2. Scale-discretised wavelets on the sphere

The scale-discretised wavelet transform aims to extract spatially localised, scale-dependent features in the signal of interest $f \in L^2(S^2)$. The j -th wavelet coefficient $W^{\Psi^j} \in L^2(S^2)$ is defined as the convolution of f with the wavelet $\Psi^j \in L^2(S^2)$:

$$\begin{aligned} W^{\Psi^j}(\omega) &\equiv (f \star \Psi^j)(\omega) \equiv \langle f | \mathcal{R}_\omega \Psi^j \rangle \\ &\equiv \int_{S^2} d\Omega(\omega') f(\omega') (\mathcal{R}_\omega \Psi^j)^*(\omega'), \end{aligned} \quad (3)$$

where $*$ denotes complex conjugation. Convolution on the sphere is defined by the inner product of f with the rotated wavelet $\mathcal{R}_\omega \Psi^j$. We restrict our attention to axisymmetric wavelets, i.e. wavelets that are azimuthally symmetric when centred on the poles. Consequently, the rotation operator $\mathcal{R}_\omega$ is parameterised by angular position $\omega = (\theta, \phi)$ only and not also orientation.⁴ For the axisymmetric case the spherical harmonic decomposition of W^{Ψ^j} is then simply given by a weighted product in harmonic space:

$$W_{\ell m}^{\Psi^j} = \sqrt{\frac{4\pi}{2\ell+1}} f_{\ell m} \Psi_{\ell 0}^{j*}, \quad (4)$$

where $W_{\ell m}^{\Psi^j} = \langle W^{\Psi^j} | Y_{\ell m} \rangle$, $f_{\ell m} = \langle f | Y_{\ell m} \rangle$ and $\Psi_{\ell 0}^j \delta_{m0} = \langle \Psi^j | Y_{\ell m} \rangle$, and where δ_{m0} is the Kronecker delta symbol.

The wavelet coefficients extract the detail information of the signal only; a scaling function and corresponding scaling coefficients must be introduced to represent the low-frequency (low- ℓ), approximate information of the signal. The scaling coefficients $W^\Phi \in L^2(S^2)$ are defined by the convolution of f with the scaling function $\Phi \in L^2(S^2)$:

$$W^\Phi(\omega) \equiv (f \star \Phi)(\omega) = \langle f | \mathcal{R}_\omega \Phi \rangle, \quad (5)$$

or in harmonic space,

$$W_{\ell m}^\Phi = \sqrt{\frac{4\pi}{2\ell+1}} f_{\ell m} \Phi_{\ell 0}^*, \quad (6)$$

where $W_{\ell m}^\Phi = \langle W^\Phi | Y_{\ell m} \rangle$ and $\Phi_{\ell 0} \delta_{m0} = \langle \Phi | Y_{\ell m} \rangle$.

Provided the wavelets and scaling function satisfy an admissibility property (defined below), the function f may be reconstructed exactly from its wavelet and scaling coefficients by

$$\begin{aligned} f(\omega) &= \int_{S^2} d\Omega(\omega') W^\Phi(\omega') (\mathcal{R}_{\omega'} \Phi)(\omega) \\ &+ \sum_{j=J_0}^J \int_{S^2} d\Omega(\omega') W^{\Psi^j}(\omega') (\mathcal{R}_{\omega'} \Psi^j)(\omega), \end{aligned} \quad (7)$$

or equivalently in harmonic space by

$$f_{\ell m} = \sqrt{\frac{4\pi}{2\ell+1}} W_{\ell m}^\Phi \Phi_{\ell 0} + \sqrt{\frac{4\pi}{2\ell+1}} \sum_{j=J_0}^J W_{\ell m}^{\Psi^j} \Psi_{\ell 0}^j. \quad (8)$$

⁴ As already noted, the extension to directional scale-discretised wavelets has been derived by Wiaux et al. (2008). At present the S2LET code supports axisymmetric wavelets only; directional wavelets will be added in a later release.

The parameters J_0, J define the lowest and highest scales j of the wavelet decomposition and must be defined consistently to extract and reconstruct all the information content of f . These parameters depend on the construction of the wavelets and scaling function and are defined explicitly in the next paragraphs. The admissibility condition under which a band-limited function f can be decomposed and reconstructed exactly is given by the following resolution of the identity:

$$\frac{4\pi}{2\ell+1} \left(|\Phi_{\ell 0}|^2 + \sum_{j=J_0}^J |\Psi_{\ell 0}^j|^2 \right) = 1, \quad \forall \ell. \quad (9)$$

We are now in position to define wavelets and a scaling function that satisfy the admissibility property. We use the smooth generating functions defined by Wiaux et al. (2008) in order to tile the harmonic line (the needlet generating functions defined by Marinucci et al. (2008) can also be used; in fact, the S2LET code supports both definitions). Consider the C^∞ Schwartz function with compact support on $[-1, 1]$:

$$s(t) \equiv \begin{cases} e^{-\frac{1}{1-t^2}}, & t \in [-1, 1] \\ 0, & t \notin [-1, 1] \end{cases}, \quad (10)$$

for $t \in \mathbb{R}$. We introduce the positive real parameter $\lambda \in \mathbb{R}_+^*$ to map $s(t)$ to

$$s_\lambda(t) \equiv s\left(\frac{2\lambda}{\lambda-1}(t-1/\lambda)-1\right), \quad (11)$$

which has compact support in $[1/\lambda, 1]$. We then define the smoothly decreasing function k_λ by

$$k_\lambda(t) \equiv \frac{\int_t^1 \frac{dr'}{r'} s_\lambda^2(r')}{\int_{1/\lambda}^1 \frac{dr'}{r'} s_\lambda^2(r')}, \quad (12)$$

which is unity for $t < 1/\lambda$, zero for $t > 1$, and is smoothly decreasing from unity to zero for $t \in [1/\lambda, 1]$. We finally define the wavelet generating function by

$$\kappa_\lambda(t) \equiv \sqrt{k_\lambda(t/\lambda) - k_\lambda(t)} \quad (13)$$

and the scaling function generating function by

$$\eta_\lambda(t) \equiv \sqrt{k_\lambda(t)}. \quad (14)$$


The wavelets and scaling function are constructed from their generating functions to satisfy the admissibility condition given by Eqn. (9). A natural approach is to define $\Psi_{\ell m}^j$ from the generating functions κ_λ to have support on $[\lambda^{j-1}, \lambda^{j+1}]$, yielding

$$\Psi_{\ell m}^j \equiv \sqrt{\frac{2\ell+1}{4\pi}} \kappa_\lambda\left(\frac{\ell}{\lambda^j}\right) \delta_{m0}. \quad (15)$$


For these wavelets, Eqn. (9) is satisfied for $\ell \geq \lambda^{J_0}$, where J_0 is the lowest wavelet scale used in the decomposition. The scaling function Φ is constructed to extract the modes that cannot be probed by the wavelets (i.e. modes with $\ell < \lambda^{J_0}$):

$$\Phi_{\ell m} \equiv \sqrt{\frac{2\ell+1}{4\pi}} \eta_\lambda\left(\frac{\ell}{\lambda^{J_0}}\right) \delta_{m0}. \quad (16)$$

To satisfy exact reconstruction, J is set to ensure the wavelets reach the band-limit of the signal of interest, yielding $J = \lceil \log_\lambda(L-1) \rceil$. The choice of the lowest wavelet scale J_0 is



(a) Tiling of the harmonic line



(b) Wavelets and scaling function on the sphere

Fig. 1: Wavelets for scales $j \in \{2, 3, 4, 5\}$ and scaling function constructed through a tiling of the harmonic line (top panel) and reconstructed on the sphere (bottom panel) for the parameters $\lambda = 3$ and $J_0 = 2$ and for band-limit $L = 128$. This plot was produced with a Matlab demo included in S2LET.

arbitrary, provided that $0 \leq J_0 < J$. The wavelets and scaling function may then be reconstructed on the sphere through an inverse spherical harmonic transform. With this construction the wavelets and scaling function are well-localised both spatially on the sphere and also in harmonic space, as shown in Figure 1. Consequently, the scale-discretised wavelet transform on the sphere can be used to extract spatially localised, scale-dependent features in the signal of interest.

3. The S2LET code

In this section we describe the S2LET code. We first introduce a multiresolution algorithm to capture each wavelet scale in the minimum number of samples on the sphere, which follows by taking advantage of the reduced band-limit of the wavelets for scales $j < J-1$. This multiresolution algorithm was introduced by Wiaux et al. (2008) already and reduces the computation cost of the transform considerably. We then provide details of the implementation, the computational complexity and the numerical accuracy of the scale-discretised wavelet transform implemented in the S2LET code. We finally outline planned future extensions of the S2LET code.

3.1. Multiresolution algorithm

In harmonic space, the wavelet coefficients are simply given by the weighted product of the spherical harmonic coefficients of f and the wavelets, as expressed in Eqn. (6). Although the wavelet coefficients can be analysed at the same resolution as the signal f (full-resolution), by construction they have different band-limits for different scales j , as shown in Figure 1. Reconstruction can thus be performed at a lower resolution without any loss of information. This approach yields a multiresolution algorithm where the wavelet coefficients are reconstructed with the minimal number of samples on the sphere: the j -th wavelet coefficients have band-limit λ^{j+1} and are thus recovered on $(\lambda^{j+1} - 1)(2\lambda^{j+1} - 1) + 1$ samples on the sphere when the MW sampling theorem is adopted.⁵ This approach leads to significant improvements in terms of speed and memory use compared to the full-resolution case, as shown in the next section. Figure 2 illustrates the use of the full-resolution and multiresolution transforms on a map of Earth topography data.

3.2. Implementation and interfaces


The core numerical routines of S2LET are implemented in C. By adopting a low level programming language such as C for the implementation of the core algorithms, computational efficiency is optimised. The C library includes the full-resolution and multiresolution wavelet transforms, with specific optimisations for real signals in order to take advantage of all symmetries of the spherical harmonic transform. The scale-discretised wavelet transform is computed in harmonic space through Eqn. (4) and Eqn. (6), for the input parameters (L, λ, J_0) . To reconstruct signals on the sphere, by default S2LET uses the exact spherical harmonic transform of the MW sampling theorem (McEwen & Wiaux 2011) implemented in the SSHT⁶ code. In this case all transforms are exact and one can analyse and synthesise real and complex signals using the MW sampling at floating-point precision. S2LET has been extended to also support the HEALPix sampling scheme. Since the spherical harmonic transform implemented in HEALPix is not theoretically exact, the scale-discretised wavelet transform computed using the HEALPix sampling does not capture all the information of a band-limited signal and is thus not theoretically exact. Nevertheless, the transforms computed using HEALPix achieve good numerical accuracy in most situations.

We provide interfaces for the C library in three languages: Matlab, IDL and Java. The Matlab and IDL codes also include routines to read/write signals on the sphere stored in either HEALPix FITS⁷ files or the FITS file format used to store MW sampled signals. In addition, functionality to plot the Mollweide projection of real signals for both MW or HEALPix samplings is included. The Java interface includes an object-oriented representation of sampled maps, spherical harmonics and wavelet transforms. All routines and interfaces are well documented and illustrated with several examples for both the MW and HEALPix samplings. These examples cover multiple combinations of parameters and types of signals. S2LET requires SSHT, which implements fast and exact algorithms to perform


⁵ When adopting the HEALPix sampling of the sphere, the HEALPix resolution parameter N_{side}^j for the wavelet coefficients of scale j can be related to the band-limit of the wavelet coefficients: e.g. $N_{\text{side}}^j = \lambda^{j+1}/2$.

⁶ <http://www.jasonmcewen.org/>

⁷ <http://fits.gsfc.nasa.gov/>



(a) Full-resolution wavelet transform



(b) Multiresolution wavelet transform

Fig. 2: Scale-discretised wavelet transform of a band-limited topography map of the Earth for $\lambda = 3$, $J_0 = 2$ and $L = 128$, i.e. with the wavelets shown in Figure 1. The wavelet transform decomposes the band-limited signal into wavelet coefficients that extract spatially localised, scale-dependent features. Since the wavelets for different scales j have different band-limits, the wavelet coefficients can be reconstructed at lower resolution on the sphere for lower scales j . Panel (a) shows the full-resolution wavelet transform of the topography map. The original Earth topography map is shown in the top-left plot, the scaling coefficients are shown in the top-right plot, while the wavelet coefficients at scales $j \in \{2, 3, 4, 5\}$ are shown left-to-right, top-to-bottom respectively in the remaining plots. Panel (b) shows the same decomposition but using the multiresolution algorithm. The signals shown in panel (b) contain the same information as in panel (a) but represented in the minimal number of samples on the sphere. These plots were produced by one of the many Matlab demos provided with S2LET.

the forward and inverse spherical harmonic transforms corresponding to the MW sampling theorem (McEwen & Wiaux 2011). SSHT in turn requires the FFTW⁸ package for the computation of fast Fourier transforms. The fast spherical harmonic transforms implemented in SSHT compute Wigner functions, and thus the spherical harmonic functions, through efficient re-

⁸ <http://www.fftw.org/>

cursion using either the method of Trapani & Navaza (2006) or Risbo (1996). Here we present results using the recursion of Risbo (1996). The fast spherical harmonic transform algorithms implemented in SSHT scale as $O(L^3)$ (McEwen & Wiaux 2011).

The complexity of the axisymmetric scale-discretised wavelet transform is dominated by spherical harmonic transforms since the wavelet transforms are computed efficiently in harmonic space, through Eqn. (4) and Eqn. (6) for the forward transform and through Eqn. (8) for the inverse transform. Given a band-limit L and wavelet parameters (λ, J_0) , recall that the maximum scale is given by $J = \lceil \log_\lambda(L - 1) \rceil$ and hence the wavelet transform (forward or inverse) involves $(J - J_0 + 3)$ spherical harmonic transforms (one for the original signal, one for the scaling coefficients and $(J - J_0 + 1)$ for the wavelet coefficients). If the scaling coefficients and all wavelet coefficients are reconstructed at full-resolution in real space, the axisymmetric scale-discretised wavelet transform scales as $O((J - J_0 + 3)L^3)$. However, in the previous section we established a multiresolution algorithm that takes advantage of the reduced band-limit of the wavelets for scales $j < J - 1$. With the multiresolution algorithm only the finest wavelet scales $j \in \{J - 1, J\}$ are computed at maximal resolution corresponding to the band-limit of the signal. The complexity of the overall multiresolution wavelet transform is then dominated by these operations and effectively scales as $O(L^3)$.

3.3. Numerical validation

We evaluate the performance of S2LET in terms of accuracy and complexity using the MW sampling theorem, for which all transforms are theoretically exact. We show that S2LET achieves floating-point precision and scales as detailed in the previous section.

We consider band-limits $L = 2^i$ with $i \in \{2, \dots, 10\}$ and generate sets of spherical harmonic coefficients $f_{\ell m}$ following independent Gaussian distributions $\mathcal{N}(0, 1)$. We then perform the wavelet decomposition and reconstruct the harmonic coefficients, denoted by $f_{\ell m}^{\text{rec}}$. We evaluate the accuracy of the transform using the error metric $\epsilon = \max |f_{\ell m} - f_{\ell m}^{\text{rec}}|$, which is theoretically zero for both transforms since all signals are band-limited by construction. The complexity is quantified by observing how the computation time $t_c = [t_{\text{synthesis}} + t_{\text{analysis}}]/2$ scales with band-limit, where the synthesis and analysis computation times are specified by $t_{\text{synthesis}}$ and t_{analysis} respectively. Since we evaluate the wavelet transform in real space, a preliminary step is required to reconstruct the signal f from the randomly generated $f_{\ell m}$. This step is not included in the computation time since its only purpose is to generate a valid band-limited test signal on the sphere. The analysis then denotes the decomposition of f into wavelet coefficients W^{ψ_j} and scaling coefficients W^{Φ} on the sphere. The synthesis refers to recovering the signal f^{rec} from these coefficients. The final step, which is not included in the computation time either, is to decompose f^{rec} into harmonic coefficients $f_{\ell m}^{\text{rec}}$ in order to compare them with $f_{\ell m}$. The stability of both ϵ and t_c is checked by averaging over hundreds of realisations of $f_{\ell m}$ for $L = 2^i$ with $i \in \{2, \dots, 8\}$ and a few realisations with $i \in \{9, 10\}$. The results proved to be very stable, i.e. the variances of the error and timing metrics are lower than 5%. Recall that for given band-limit L the number of samples on the sphere required by the exact quadrature is $(2L - 1)(L - 1) + 1$. All tests were run on an Intel 2.0GHz Core i7 processor with 8GB of RAM.




Fig. 3: Numerical accuracy and computation time of the scale-discretised wavelet transform computed with S2LET. We consider $L = 2^i$ with $i \in \{2, \dots, 10\}$, with parameters $\lambda = 2$, $J_0 = 0$. These results are averaged over many realisations of random band-limited signals and were found to be very stable. The scale-discretised transform is either performed at full-resolution (solid lines) or with the multiresolution algorithm (dashed lines). Very good numerical accuracy is achieved by both the full-resolution and multiresolution algorithms (which achieve indistinguishable accuracy), with numerical errors comparable to floating-point precision, found empirically to scale as $O(L)$ as shown by the red line in panel (a). Computation time scales as $O(L^3)$ for both algorithms as shown by the red line in panel (b), in agreement with theory. The multiresolution algorithm is four to five times faster than the full-resolution approach for the band-limits considered.

The accuracy and timing performance of the scale-discretised wavelet transform implemented in S2LET are presented in Figure 3. S2LET achieves very good numerical accuracy, with numerical errors comparable to floating-point precision. Moreover, the full-resolution and multiresolution algorithms are indistinguishable in terms of accuracy. However, the latter is four to five times faster than the former for the band-limits considered since only the wavelet coefficients for $j \in \{J - 1, J\}$ are computed at full-resolution. As shown in Figure 3, computation time scales as $O(L^3)$ for both algorithms, in agreement with theory.

3.4. Future extensions

We have restricted this work to axisymmetric scale-discretised wavelets so that the rotation operator is only parametrised by angular position on the sphere and not also orientation. The extension to directional wavelets has already been considered by Wiaux et al. (2008) but has not yet been implemented in the S2LET code. In future work we plan to relax this constraint and to consider directional, steerable wavelets on the sphere (Wiaux et al. 2008). We also plan to exploit recent ideas leading to

fast (spin) spherical harmonic transforms (McEwen & Wiaux 2011) to yield faster algorithms than those developed by Wiaux et al. (2008) to compute directional wavelet transforms on the sphere. Finally, we intend to add support to analyse spin signals on the sphere. In a future release, the code will also be parallelised, which will lead to further speed improvements, and a more complete framework in Java will be added, including IO and plotting routines. The S2LET code will thus be under active development with future releases forthcoming. In any case, we hope this first version of the S2LET code will prove useful for axisymmetric scale-discretised wavelet analysis on the sphere. Indeed, the code has already been used as an integral part of the new exact flaglet wavelet transform on the ball (Leistedt & McEwen 2012), the spherical space constructed by augmenting the sphere with the radial line.

4. Examples

The S2LET code is extensively documented and ships with several examples in the four languages supported. In this section we present a subset of short examples, along with the code to execute them in order to demonstrate the ease of using S2LET to perform wavelet transforms.⁹

4.1. Wavelet transform from the command line

S2LET includes ready-to-use high-level programs to directly decompose a real signal into wavelet coefficients. The inputs are a FITS file containing the signal of interest and the parameters for the transform. The program writes the output coefficients in FITS files in the same directory as the input file and with a consistent naming scheme. These commands are available for both sampling schemes. For the MW sampling case illustrated in Example 1, the wavelet transform is exact and the band limit corresponds to the resolution of the input map, which will be read automatically from the file. The transform may be performed in full-resolution or multiresolution by adjusting the multiresolution flag specified by the last parameter (respectively 0 and 1), and the output wavelet coefficients are computed at full and minimal resolution accordingly. For the case of a HEALPix map, as illustrated in Example 2, the transform is not exact and the band-limit must be supplied as the last parameter in the command. The output scaling and wavelet coefficients of a HEALPix map are reconstructed and stored in FITS files at the same resolution as the input map. For both MW and HEALPix samplings the output coefficients may be read and plotted using the Matlab or IDL routines.

```
>> ./bin/s2let_axisym_mw_analysis_real
    <inputFitsFile> <lambda> <J_0>
    <multiresFlag>
>> ./bin/s2let_axisym_mw_synthesis_real
    <outputRoot> <lambda> <J_0> <bandLimit>
```

Example 1: Performing the forward (analysis) and inverse (synthesis) wavelet transform of a real signal (MW sampling) from the command line.

⁹ Note that the code uses a slightly different notation compared to the equations of this article: B refers to the wavelet scaling parameter (denoted λ herein) and $J_{\min}$ to the first scale of the transform (denoted J_0 herein).

```
>> ./bin/s2let_axisym_hpx_analysis_real
    <inputFitsFile> <lambda> <J_0>
    <bandLimit>
>> ./bin/s2let_axisym_hpx_synthesis_real
    <outputRoot> <lambda> <J_0> <bandLimit>
```

Example 2: Performing the forward (analysis) and inverse (synthesis) wavelet transform of a real signal (HEALPix sampling) from the command line.

```
% Example: Wavelet transform in Matlab
lambda = 3; J0 = 2; L = 192;
Jmax = s2let_jmax(L, lambda);

% Read a real HEALPix map from a FITS file
inputfile = 'data/somecmbsimu_hpx_128.fits';
[f, nside] =
    s2let_hpx_read_real_map(inputfile);

% Perform the wavelet transform
[f_wav, f_scal] = s2let_axisym_hpx_analysis
    (f, 'B', lambda, 'L', L, 'J_min', J0);

% Plot the map and the wavelet coefficients
figure; ns = ceil(sqrt(2+Jmax-J0+1));
subplot(ns, ns, 1);
s2let_hpx_plot_mollweide(f);
title('Initial band-limited data')
subplot(ns, ns, 2);
s2let_hpx_plot_mollweide(f_scal);
title('Scaling fct')
for j = J0:Jmax
    subplot(ns, ns, j-J0+3);
    s2let_hpx_plot_mollweide(f_wav{j-J0+1});
    title(['Wavelet scale :', int2str(j)-J0+1])
end
```

Example 3: Performing the wavelet transform of a real signal (HEALPix sampling) using the Matlab interface.

4.2. Wavelet transform in Matlab and IDL

Examples 3 and 4 read real signals on the sphere from FITS files, calculate the wavelet coefficients and plot them using a Mollweide projection. The first case is a Matlab example where the input map is a simulation of the cosmic microwave background in the HEALPix sampling. The second case is a IDL example where the input map is a topography map of the Earth in MW sampling. S2LET ships with versions of these two examples in C, Matlab and IDL.

4.3. Wavelet denoising in C

Example 5 illustrates the use of the wavelet transform to denoise a signal on the sphere. The input noisy map is a band-limited topography map of the Earth in MW sampling at resolution $L = 128$. It is read from a FITS file, decomposed into wavelet coefficients (for given parameters λ and J_0) which are then denoised by thresholding. The denoised signal is reconstructed from the denoised wavelet coefficients and written to a FITS file.

In this example we consider a noisy signal $y = s + n \in L^2(S^2)$, where the signal of interest $s \in L^2(S^2)$ is contaminated with noise $n \in L^2(S^2)$. We consider zero-mean white Gaussian noise on the sphere, where the variance of the harmonic coefficients of

```

; Example: Wavelet transform in IDL
lambda = 3
J0 = 2

; Read a real MW map from a FITS file
file = 'data/earth_tomo_mw_128.fits'
f = s2let_mw_read_real_map(file)
L = s2let_get_mw_bandlimit(f)
Jmax = s2let_j_max(L, lambda)

; Perform the wavelet transform
f_wav = s2let_axisym_mw_wav_analysis_real
        (f, lambda, J0)
f_rec = s2let_axisym_mw_wav_synthesis_real
        (f_wav)

; Plot the map and the wavelet coefficients
ns = ceil(sqrt(3+Jmax-J0))
!P.MULTI=[0,ns,ns]
s2let_mw_plot_mollweide, f_rec,
    title='Band-limited map'
s2let_mw_plot_mollweide, f_wav.scal,
    title='Scaling map'
for j=0, Jmax-J0 do begin
    s2let_mw_plot_mollweide, f_wav.(j),
        title='Wavelet map '+strtrim(j+1,2)+'
        on '+'strtrim(Jmax-J0+1,2)
endfor
!P.MULTI=0

```

Example 4: Performing the wavelet transform of a real signal (MW sampling) using the IDL interface.

the noise is specified by

$$\mathbb{E}(|n_{\ell m}|^2) = \sigma^2, \quad \forall \ell, m. \quad (17)$$

A simple way to evaluate the fidelity of the observed signal y is through the signal-to-noise ratio (SNR), which we define on the sphere by

$$\text{SNR}(y) \equiv 10 \log_{10} \frac{\|s\|_2^2}{\|y - s\|_2^2}, \quad (18)$$

where the signal energy is defined by


$$\|y\|_2^2 \equiv \langle y|y \rangle = \int_{S^2} d\Omega(\omega) |y(\omega)|^2 = \sum_{\ell m} |y_{\ell m}|^2. \quad (19)$$

We seek a denoised version of y , denoted by $d \in L^2(S^2)$, with large $\text{SNR}(d)$ so that d isolates the informative signal s . When taking the wavelet transform of the noisy signal y , one expects the energy of the informative part to be concentrated in a small number of wavelet coefficients while the noise energy should be spread over various wavelet scales. Since the transform is linear, the wavelet coefficients of the j -th scale are simply given by the sum of the individual contributions:


$$Y^j(\omega) = S^j(\omega) + N^j(\omega), \quad (20)$$

where capital letters denote the wavelet coefficients, i.e. $Y^j \equiv y \star \Psi^j$, $S^j \equiv s \star \Psi^j$ and $N^j \equiv n \star \Psi^j$. For the zero-mean white Gaussian noise defined by Eqn. 17, the noise in wavelet space is also zero-mean and Gaussian, with variance


$$\mathbb{E}(|N^j(\omega)|^2) = \sigma^2 \sum_{\ell} |\Psi_{\ell 0}^j|^2 \equiv (\sigma^j)^2.$$



(a) Band-limited signal



(b) Noisy signal with $\text{SNR}(y) = 11.8\text{dB}$



(c) Denoised signal with $\text{SNR}(d) = 14.6\text{dB}$

Fig. 4: Scale-discretised wavelet denoising by hard-thresholding.

Denoising is performed by hard-thresholding the wavelet coefficients Y^j , where the threshold is taken as $T^j = 3\sigma^j$. The denoised wavelet coefficients $D^j \equiv d \star \Psi^j$ are thus given by

$$D^j(\omega) = \begin{cases} 0, & \text{if } Y^j(\omega) < T^j(\omega) \\ Y^j(\omega), & \text{otherwise} \end{cases}. \quad (21)$$

The denoised signal $d \in L^2(S^2)$ is reconstructed from its wavelet coefficients D^j and the scaling coefficients of y , which are not thresholded. The denoising procedure outlined above is particularly simple and more sophisticated denoising strategies can be developed; we adopt this simple denoising strategy merely to illustrate the use of the S2LET code. In this example we perform the wavelet transform with parameters $\lambda = 2$ and $J_0 = 0$. For a noisy signal y with $\text{SNR}(y) = 11.8\text{dB}$, the scale-discretised wavelet denoising recovers a denoised signal d with $\text{SNR}(d) = 14.6\text{dB}$. The initial, noisy and denoised maps are shown in Figure 4.

5. Summary

In the era of precision astrophysics and cosmology, large and complex data-sets on the sphere must be analysed at high preci-

```
// Example: Wavelet denoising in C
int lambda = 2, J0 = 0;

// Read a real MW map from a FITS file
char inputfile[100] = "...";
double *f;
int L = s2let_fits_read_mw_bandlimit(file);
s2let_mw_allocate_real(&f, L);
s2let_fits_read_mw_map(f, file, L);

// Perform multiresolution wavelet analysis
double *f_wav, *f_scal;
s2let_axisym_mw_allocate_f_wav_multires_real
(&f_wav, &f_scal, lambda, L, J0);
s2let_axisym_mw_wav_analysis_multires_real
(f_wav, f_scal, g, lambda, L, J0);

// Threshold the wavelets with a noise model
s2let_axisym_wav_hardthreshold_multires_real
(f_wav, threshold, lambda, L, J0);

// Reconstruct the denoised signal
double *f_denoised;
s2let_mw_allocate_real(&f_denoised, L);
s2let_axisym_mw_wav_synthesis_multires_real
(f_denoised, f_wav, f_scal, lambda, L, J0);

// Write the denoised signal
char outputfile[100] = "...";
s2let_fits_write_mw_map(outfile, f_denoised, L);
```

Example 5: Denoising a real signal (MW sampling) in C through hard-thresholding of the wavelet coefficients.

sion in order to confront accurate theoretical predictions. Scale-discretised wavelets are a powerful analysis technique where spatially localised, scale-dependent signal features of interest can be extracted and analysed. Combined with a sampling theorem, this framework leads to an exact multiresolution wavelet analysis, where signals on the sphere can be reconstructed from their scaling and wavelet coefficients exactly.

We have described S2LET, a fast and robust implementation of the scale-discretised wavelet transform. Although the first public release of S2LET is restricted to axisymmetric wavelets, the generalisation to directional, steerable wavelets will be made available in a future release. The core numerical routines of S2LET are written in C and have interfaces in Matlab, IDL and Java. Both MW and HEALPix pixelisation schemes are supported. In this article we have presented a number of examples to illustrate the ease of use of S2LET for performing wavelet transform of real signals stored as FITS files and to plot scaling and wavelet coefficients on Mollweide projections of the sphere. We have also detailed a denoising example where denoising is performed through simple hard-thresholding in wavelet space. Although only a simple denoising strategy was performed to illustrate the use of the S2LET code, it nevertheless performed very well, highlighting the effectiveness of the scale-discretised wavelet transform on the sphere.

References

- Antoine, J.-P. & Vandergheynst, P. 1998, *J. Math. Phys.*, 39, 3987
 Antoine, J.-P. & Vandergheynst, P. 1999, *Applied Comput. Harm. Anal.*, 7, 1
 Baldi, P., Kerkycharian, G., Marinucci, D., & Picard, D. 2009, *Annals of Statistics*, 37 No.3, 1150
 Barreiro, R. B., Hobson, M. P., Lasenby, A. N., et al. 2000, *Mon. Not. Roy. Astron. Soc.*, 318, 475

- Basak, S. & Delabrouille, J. 2012, *Mon. Not. Roy. Astron. Soc.*, 419, 1163
 Cayón, L., Sanz, J. L., Martínez-González, E., et al. 2001, *Mon. Not. Roy. Astron. Soc.*, 326, 1243
 Daubechies, I. 1992, *Ten Lectures on Wavelets* (Society for Industrial and Applied Mathematics)
 Deriaz, E., Starck, J.-L., & Pires, S. 2012, *Astron. & Astrophys.*, 540, A34
 Doroshkevich, A. G., Naselsky, P. D., Verkhodanov, O. V., et al. 2005, *International Journal of Modern Physics D*, 14, 275
 Driscoll, J. R. & Healy, D. M. J. 1994, *Advances in Applied Mathematics*, 15, 202
 Górski, K. M., Hivon, E., Banday, A. J., et al. 2005, *ApJ*, 622, 759
 Healy, D., Jr., Rockmore, D., Kostelec, P. J., & Moore, S. S. B. 1996, *The Journal of Fourier Analysis and Applications*, 9, 341
 Labatie, A., Starck, J. L., & Lachièze-Rey, M. 2012, *Astron. J.*, 746, 172
 Lan, X. & Marinucci, D. 2008, *Electronic Journal of Statistics*, 2, 332
 Leistedt, B. & McEwen, J. D. 2012, *IEEE Trans. Sig. Proc.*, 60
 Marinucci, D., Pietrobon, D., Balbi, A., et al. 2008, *Mon. Not. Roy. Astron. Soc.*, 383, 539
 McEwen, J. D., Hobson, M. P., & Lasenby, A. N. 2006, *Arxiv preprint astro-ph/0609159*
 McEwen, J. D., Hobson, M. P., Lasenby, A. N., & Mortlock, D. J. 2006, *Mon. Not. Roy. Astron. Soc.*, 371, L50
 McEwen, J. D., Vielva, P., Hobson, M. P., Martínez-González, E., & Lasenby, A. N. 2007a, *Mon. Not. Roy. Astron. Soc.*, 376, 1211
 McEwen, J. D., Vielva, P., Wiaux, Y., et al. 2007b, *J. Fourier Anal. and Appl.*, 13, 495
 McEwen, J. D. & Wiaux, Y. 2011, *IEEE Trans. Sig. Proc.*, 59, 5876
 McEwen, J. D., Wiaux, Y., Hobson, M. P., Vandergheynst, P., & Lasenby, A. N. 2008, *Mon. Not. Roy. Astron. Soc.*, 384, 1289
 Narcowich, F. J., Petrushev, P., & Ward, J. D. 2006, *SIAM J. Math. Anal.*, 38, 574
 Pietrobon, D., Amblard, A., Balbi, A., et al. 2008, *Phys. Rev. D*, 78, 103504
 Pietrobon, D., Balbi, A., Cabella, P., & Gorski, K. M. 2010, *Astrophys. J.*, 723, 1
 Risbo, T. 1996, *Journal of Geodesy*, 70, 383
 Schmitt, J., Starck, J. L., Casandjian, J. M., Fadili, J., & Grenier, I. 2010, *Astron. & Astrophys.*, 517, A26
 Schröder, P. & Sweldens, W. 1995, *Computer Graphics Proceedings (SIGGRAPH 95)*, 161
 Starck, J.-L., Moudden, Y., Abrial, P., & Nguyen, M. 2006a, *Astron. & Astrophys.*, 446, 1191
 Starck, J.-L., Pires, S., & Réfrégier, A. 2006b, *Astron. & Astrophys.*, 451, 1139
 Sweldens, W. 1996, *Appl. Comput. Harmon. Anal.*, 3, 186
 Sweldens, W. 1997, *SIAM J. Math. Anal.*, 29, 511
 Trapani, S. & Navaza, J. 2006, *Acta Crystallographica Section A*, 62, 262
 Vielva, P., Martínez-González, E., Barreiro, R. B., Sanz, J. L., & Cayón, L. 2004, *Astrophys. J.*, 609, 22
 Vielva, P., Martínez-González, E., & Tucci, M. 2006a, *Mon. Not. Roy. Astron. Soc.*, 365, 891
 Vielva, P., Wiaux, Y., Martínez-González, E., & Vandergheynst, P. 2006b, *New A Rev.*, 50, 880
 Vielva, P., Wiaux, Y., Martínez-González, E., & Vandergheynst, P. 2007, *MNRAS*, 381, 932
 Wiaux, Y., Jacques, L., & Vandergheynst, P. 2005, *Astrophys. J.*, 632, 15
 Wiaux, Y., Jacques, L., Vielva, P., & Vandergheynst, P. 2006, *Astrophys. J.*, 652, 820
 Wiaux, Y., McEwen, J. D., Vandergheynst, P., & Blanc, O. 2008, *Mon. Not. Roy. Astron. Soc.*, 388, 770
 Wiaux, Y., McEwen, J. D., & Vielva, P. 2007, *J. Fourier Anal. and Appl.*, 13, 477
 Wiaux, Y., Vielva, P., Barreiro, R. B., Martínez-González, E., & Vandergheynst, P. 2008, *MNRAS*, 385, 939
 Wiaux, Y., Vielva, P., Martínez-González, E., & Vandergheynst, P. 2006, *Physical Review Letters*, 96, 151303
 Yeo, B., Ou, W., & Golland, P. 2008, *Image Processing, IEEE Transactions on*, 17, 283

Acknowledgements. BL is supported by the Perren Fund and the Impact Fund. JDM is supported by a Newton International Fellowship from the Royal Society and the British Academy. YW is supported by the Center for Biomedical Imaging (CIBM) of the Geneva and Lausanne Universities, EPFL and the Leenaards and Louis-Jeantet foundations.